

# Accéder au menu démarrage (Boot Menu) et/ou BIOS

Source : [https://forum.pcastuces.com/comment\\_acceder\\_au\\_boot\\_menu\\_ou\\_et\\_au\\_bios\\_uefi\\_differeentes\\_marques\\_de\\_pc-f4s85637.htm](https://forum.pcastuces.com/comment_acceder_au_boot_menu_ou_et_au_bios_uefi_differeentes_marques_de_pc-f4s85637.htm)

Manufacturer	Type	Models	Boot Menu	Boot Once	BIOS/UEFI Key	Change Priority
Acer			<u>Esc</u> , <u>F12</u> , <u>F9</u>		Del, F2	
Acer	netbook	Aspire One zg5, zg8	<u>F12</u>		F2	
Acer	netbook	Aspire Timeline	<u>F12</u>		F2	
Acer	netbook	Aspire v3, v5, v7	<u>F12</u>	The "F12 Boot Menu" must be enabled in BIOS. It is disabled by default.	<u>F2</u>	
Manufacturer	Type	Models	Boot Menu	Boot Once	BIOS/UEFI Key	Change Priority
Apple		After 2006	<u>Option</u>			
Manufacturer	Type	Models	Boot Menu	Boot Once	BIOS/UEFI Key	Change Priority
Asus	desktop		<u>F8</u>		F9	
Asus	laptop	VivoBook f200ca, f202e, q200e, s200e, s400ca, s500ca, u38n, v500ca, v550ca, v551, x200ca, x202e, x550ca, z202e	<u>Esc</u>		Delete	
Asus	laptop	N550JV, N750JV, N550LF, Rog g750jh, Rog g750jw, Rog g750jx	<u>Esc</u>	Disable "Fast Boot" and "Secure Boot Control" in order to boot from MBR formatted media.	F2	
Asus	laptop	Zenbook Infinity ux301, Infinity ux301la, Prime ux31a, Prime ux32vd, R509C, Taichi 21, Touch u500vz, Transformer Book TX300	<u>Esc</u>	Disable "Fast Boot" and "Secure Boot Control" in order to boot from MBR formatted media.	F2	
Asus	notebook	k25f, k35e, k34u, k35u, k43u, k46cb, k52f, k53e, k55a, k60ij, k70ab, k72f, k73e, k73s, k84l, k93sm, k93sv, k95vb, k501, k601, R503C, x32a, x35u,	<u>F8</u>		DEL	

		x54c, x61g, x64c, x64v, x75a, x83v, x83vb, x90, x93sv, x95gl, x101ch, x102ba, x200ca, x202e, x301a, x401a, x401u, x501a, x502c, x750ja				
Asus	netbook	Eee PC 1015, 1025c	<u>Esc</u>		F2	Boot Tab, Boot Device Priority, 1st Boot Device, Removable Device, F10
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Compaq		Presario	<u>Esc, F9</u>		F10	BIOS "Advanced Tab", Boot Order
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Dell	desktop	Dimension, Inspiron, Latitude, Optiplex	<u>F12</u>	Select "USB Flash Drive".	F2	
Dell	desktop	Alienware Aurora, Inspiron One 20, Inspiron 23 Touch, Inspiron 620, 630, 650, 660s, Inspiron 3000, X51, XPS 8300, XPS 8500, XPS 8700, XPS 18 Touch, XPS 27 Touch	<u>F12</u>	Select "USB Flash Drive".	F2	
Dell	desktop	Inspiron One 2020, 2305, 2320, 2330 All-In-One	<u>F12</u>	Select "USB Flash Drive".	F2	
Dell	laptop	Inspiron 11 3000 series touch, 14z Ultrabook, 14 7000 series touch, 15z Ultrabook touch, 15 7000 series touch, 17 7000 series touch	<u>F12</u>	Select "USB Storage Device"	F2	Settings->General->Boot Sequence->"USB Storage Device", then up arrow, [Apply]--[Exit]
Dell	laptop	Inspiron 14R non-touch, 15 non-touch, 15R non-touch, 17 non-touch, 17R non-touch	<u>F12</u>	Select "USB Storage Device"	F2	Settings->General->Boot Sequence->"USB Storage Device", then up arrow, [Apply]--[Exit]
Dell	laptop	Latitude c400, c600, c640, d610, d620, d630, d830, e5520, e6320, e6400, e6410, e6420, e6430, e6500, e6520, 6430u Ultrabook, x300	<u>F12</u>	Select "USB Storage Device" from boot menu.	F2	
Dell	laptop	Precision m3800, m4400, m4700, m4800, m6500, m6600, m6700, m6800	<u>F12</u>	Select "USB Storage Device" from boot menu.	F2	

Dell	laptop	Alienware 14, Alienware 17, Alienware 18, XPS 11 2-in-1, XPS 12 2-in-1, XPS 13, XPS 14 Ultrabook, XPS 15 Touch,	<u>F12</u>	Select "USB Storage Device" from boot menu.	F2	
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
eMachines			<u>F12</u>		Tab, Del	
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Fujitsu			<u>F12</u>		F2	
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
HP	generic		<u>Esc, F9</u>		Esc, F10, F1	
HP	desktop	Pavilion Media Center a1477c	<u>Esc</u>		F10	BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive"
HP	desktop	Pavilion 23 All In One	<u>Esc</u>	Select boot media from the menu.	F10	UEFI/BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive". For non-UEFI media, disable secure boot and enable legacy support.
HP	desktop	Pavilion Elite e9000, e9120y, e9150t, e9220y, e9280t	<u>Esc, F9</u>		F10	
HP	desktop	Pavilion g6 and g7	<u>Esc</u>		F10	UEFI/BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive"
HP	desktop	Pavilion HPE PC, h8-1287c	<u>Esc</u>	Then F9 for "Boot Menu"	Esc	F10, Storage tab, Boot Order, Legacy Boot Sources
HP	desktop	Pavilion PC, p6 2317c	<u>Esc</u>	Then F9 for "Boot Menu"	Esc	F10, Storage tab, Boot Order, Legacy Boot Sources
HP	desktop	Pavilion PC, p7 1297cb	<u>Esc</u>	Then F9 for "Boot Menu"	Esc	F10, Storage tab, Boot Order, Legacy Boot Sources
HP	desktop	TouchSmart 520 PC	<u>Esc</u>	Then F9 for "Boot Menu"	Esc	F10, Storage tab, Boot Order, Legacy Boot Sources

HP	laptop	2000	<u>Esc</u>	Then F9 for "Boot Menu". Select "Patriot Memory" on the Boot Option Menu.	Esc	Then F10, Storage tab, Boot Order, Legacy Boot Sources
HP	notebook	Pavilion g4	<u>Esc</u>		F10	BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive"
HP	notebook	ENVY x2, m4, m4-1015dx, m4-1115dx, sleekbook m6, m6-1105dx, m6-1205dx, m6-k015dx, m6-k025dx, touchsmart m7	<u>Esc</u>	Then F9 for "Boot Menu"	Esc	Then F10, Storage tab, Boot Order, Legacy Boot Sources
HP	notebook	Envy, dv6 and dv7 PC, dv9700, Spectre 14, Spectre 13	<u>Esc</u>	Then F9 for "Boot Menu"	Esc	Then F10, Storage tab, Boot Order, Legacy Boot Sources
HP	notebook	2000 - 2a20nr, 2a53ca, 2b16nr, 2b89wm, 2c29wm, 2d29wm	<u>Esc</u>	Then F9 for "Boot Menu"	Esc	Then F10, Storage tab, Boot Order, Legacy Boot Sources
HP	notebook	Probook 4520s, 4525s, 4540s, 4545s, 5220m, 5310m, 5330m, 5660b, 5670b	<u>Esc</u>		F10	BIOS "Advanced" tab, Boot Order, Move "USB Device" before "Hard Drive"
HP	tower	Pavilion a410n	<u>Esc</u>		F1	BIOS "Boot" tab, Boot Device Priority, Hard Drive Boot Priority, Move "USB-HDD0" up to #1 position.
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Intel			<u>F10</u>			
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Lenovo	desktop		<u>F12, F8, F10</u>		F1, F2	
Lenovo	laptop		<u>F12</u>		F1, F2	
Lenovo	laptop	ThinkPad edge, e431, e531, e545, helix, l440, l540, s431, t440s, t540p, twist, w510, w520, w530, w540, x140, x220, x230, x240, X1 carbon	<u>F12</u>		F1	
Lenovo	laptop	IdeaPad s300, u110, u310 Touch, u410, u510, y500, y510, yoga 11, yoga 13, z500	<u>Novo button</u>	Small button on the side next to the power button.	Novo button	Small button on the side next to the power button.

Lenovo	laptop	IdeaPad P500	<u>F12 or Fn + F11</u>		F2	
Lenovo	netbook	IdeaPad S10-3	<u>F12</u>		F2	
Lenovo	notebook	g460, g470, g475, g480, g485	<u>F12</u>		F2	
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
NEC			<u>F5</u>		F2	
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Packard Bell			<u>F8</u>		F1, Del	
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Samsung			<u>F12, Esc</u>			
Samsung	netbook	NC10	<u>Esc</u>		F2	Boot Tab, Select "Boot Device Priority", Press Return, Up/Down to Highlight, F6/F5 to change priority.
Samsung	notebook	np300e5c, np300e5e, np350v5c, np355v5c, np365e5c, np550p5c	<u>Esc</u>		F2	Boot Tab, Select "Boot Device Priority", Press Return, Up/Down to Highlight, F6/F5 to change priority.
Samsung	ultrabook	Series 5 Ultra, Series 7 Chronos, Series 9 Ultrabook	<u>Esc</u>	Note that you must first disable fast boot in BIOS/UEFI to boot from a USB drive.	F2	Boot Tab, Select "Boot Device Priority", Press Return, Up/Down to Highlight, F6/F5 to change priority.
Samsung	ultrabook	Ativ Book 2, 8, 9	<u>F2</u>	Note that you must first disable fast boot in BIOS/UEFI to boot from a USB drive or use the F2 boot menu.	F10	Boot Tab, Select "Boot Device Priority", Press Return, Up/Down to Highlight, F6/F5 to change priority.
<b>Manufacturer</b>	<b>Type</b>	<b>Models</b>	<b><u>Boot Menu</u></b>	<b>Boot Once</b>	<b>BIOS/UEFI Key</b>	<b>Change Priority</b>
Sharp					F2	

Manufacturer	Type	Models	Boot Menu	Boot Once	BIOS/UEFI Key	Change Priority
Sony		VAIO Duo, Pro, Flip, Tap, Fit	assist button		assist button	
Sony		VAIO, PCG, VGN	F11		F1, F2, F3	
Sony		VGN	Esc, F10		F2	BIOS "BOOT" section, "External Device Boot" enabled
Manufacturer	Type	Models	Boot Menu	Boot Once	BIOS/UEFI Key	Change Priority
Toshiba	laptop	Kira, Kirabook 13, Ultrabook	F12		F2	
Toshiba	laptop	Qosmio g30, g35, g40, g50	F12		F2	
Toshiba	laptop	Qosmio x70, x75, x500, x505, x870, x875, x880	F12		F2	
Toshiba		Protege, Satellite, Tecra	F12		F1, Esc	
Toshiba		Equium	F12		F12	

## **Modifier ordre démarrage dans BIOS UEFI :**

### **Dans l'onglet BOOT**

Inhiber **Fast Boot** et autoriser **Launch CSM**

Dans **Launch CSM** autoriser **Launch PXE OpROM**

### **Dans l'onglet Security :**

Inhiber **Secure Boot Control**

### **Dans l'onglet BOOT :**

Le Graveur DVD doit apparaître en 3ème position, le laisser en place

### **Dans l'onglet Save & Exit :**

Sélectionner **Lanch EFI from file system device** et valider

[size=2]Rebooter en maintenant ESC appuyé (sélection du Boot device pour un ASUS)

[size=2]Le Graveur y est maintenant présent, le sélectionner en ayant placé un DVD system en 64 Bits uniquement

Le Boot s'effectue alors à partir du DVD